

In the Claims:

Please cancel claims 32-34, without prejudice.

Please amend claims 2, 4-6, 8-24, 37, 38, 42, 43 and 46-48 as follows:

1. (Original) An antenna structure which receives a radio wave to be used inside a metal outer casing, said antenna structure being characterized by having a structure wherein a coil is wound about a magnetic core and being able to receive a magnetic flux from outside said metal outer casing.

2. (Currently Amended) An antenna structure which receives a radio wave to be used inside a metal outer casing, said antenna structure being characterized in that said antenna structure comprising a main magnetic path in which a coil is wound about a magnetic core and a sub-magnetic path in which said coil is not wound about said magnetic core, said magnetic path formed along said magnetic core having a configuration similar to a closed loop like configuration, a gap is provided in a part of said magnetic path of said antenna structure forming said closed loop like configuration, said gap portion of said magnetic path is configured to have magnetic resistance or magnetic permeability being different from ~~that~~that of other parts of said magnetic path, and said antenna structure has a structure wherein a magnetic flux coming from outside said metal outer casing, can be received but said magnetic flux generated by resonance hardly leaks to an outside of said magnetic path.

3. (Original) An antenna structure according to claims 1 or 2, wherein said magnetic resistance of said sub-magnetic path is configured so as to be larger than that of said magnetic resistance of said main magnetic path.

4. (Currently Amended) An antenna structure according to ~~any one of claims 1 to 3~~claim 2, wherein a material different from said material forming said magnetic core is configured to be arranged inside of said gap.

5. (Currently Amended) An antenna structure according to ~~any one of claims 1 to 4~~claim 2, wherein said gap is filled with a material different from said material forming said magnetic core.

6. (Currently Amended) An antenna structure according to ~~any one of claims 1 to 4~~claim 2, wherein said gap is an air gap.

7. (Original) An antenna structure according to claim 6, wherein said air gap is formed by inserting an intervening spacer within said gap.

8. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 7~~claim 1 or 2, wherein said antenna structure receives said radio wave including a  
long wave whose frequency is not more than 2000 KHz.

9. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 8~~claims 1 or 2, wherein said metal outer casing is formed by at least one member  
which is selected from a structure being capable of storing said antenna structure inside  
thereof and comprising a side section and a bottom cover section each of which being made  
of a metal material, respectively and a structure being capable of storing said antenna  
structure inside thereof and comprising a piece of metal member in which a side section and  
a bottom cover section being integrally formed into one piece member.

10. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 9~~claim 2, wherein a cross section of said main magnetic path is different from  
that of said sub-magnetic path.

11. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 10~~claim 2, wherein a material of said main magnetic path being different from  
that of said sub-magnetic path.

12. (Currently Amended) An antenna structure according to ~~any one of~~ ~~claims 1 to 11~~claim 2, wherein effective permeability of said sub-magnetic path is configured so as to be smaller than that of said main magnetic path.

13. (Currently Amended) An antenna structure according to ~~any one of~~ ~~claims 1 to 12~~claim 2, wherein a film layer selected from a group consisting of a magnetic transmuted film layer, a non-magnetic film layer, and a film layer having low magnetic permeability, is formed on at least a part of a surface of said sub-magnetic path or of said main magnetic path.

14. (Currently Amended) An antenna structure according to ~~any one of~~ ~~claims 1 to 13~~claim 2, wherein said main magnetic path and said sub-magnetic path form the unit members, respectively and each being independent from each other, and said main magnetic path and said sub-magnetic path are integrally connected with each other, after said coil is wound about said main magnetic path.

15. (Currently Amended) An antenna structure according to ~~any one of~~ ~~claims 1 to 14~~claim 2, wherein said gap is formed in at least one of connected portions formed between said main magnetic path and said sub-magnetic path.

16. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 14~~claim 2, wherein said gap is formed in a part of said sub-magnetic path.

17. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 16~~claim 2, wherein a connected surface of said gap, which is provided in said  
sub-magnetic path, or a connected surface formed between an end face of said main magnetic  
path and an end face of said sub-magnetic path, forms with a tapered configuration.

18. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 17~~claim 2, wherein said gap is formed by either one of ways in which the end  
faces of said main magnetic path and said sub-magnetic path being oppositely arranged to  
each other or a part of a surface of a portion of said sub-magnetic path and a part of a surface  
of other portion thereof, each of said surfaces being ones other than said end surfaces of said  
sub-magnetic path, being oppositely arranged to each other.

19. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 18~~claim 2, wherein said gap is formed in a portion where at least a part of said  
main magnetic path and at least a part of said sub-magnetic path are adjacently arranged to  
each other while in parallelism with each other.

20. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 19~~claim 2, wherein said gap is formed in a portion of said magnetic pass except  
for a portion in the vicinity of a portion of said main magnetic path on which a coil is wound.

21. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 20~~claim 2, wherein said gap includes a member whose magnetic resistance differs  
from said magnetic resistance of a material forming said magnetic path.

22. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 21~~claim 2, wherein said gap is filled with a member which is the one selected  
from a group consisting of a non-metallic and a non-magnetic material, and a non-metallic  
and magnetic transmuted material.

23. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 22~~claim 2, wherein said main magnetic path or said sub-magnetic path is made of  
a soft magnetic material.

24. (Currently Amended) An antenna structure according to ~~any one of~~  
~~claims 1 to 23~~claim 2, wherein said main magnetic path is arranged so that said main  
magnetic path takes a position at which said main magnetic path directly facing to a direction

from which said radio wave would come, with respect to said sub-magnetic path, so that said main magnetic path mainly can receive said radio wave rather than said sub-magnetic path can do.

25. (Original) An antenna structure according to claim 24, wherein a length of said main magnetic path is configured to be longer than said length of said sub-magnetic path, thereby said main magnetic path is arranged so as to cover said sub-magnetic path so that said sub-magnetic path is not directly opposed to said direction from which said radio wave is coming.

26. (Original) An antenna structure for receiving a radio wave which includes at least a magnetic core and a coil unit provided in at least a part of said magnetic core, said antenna structure characterized in that said antenna structure includes a main magnetic path wherein a coil is wound about said magnetic core and a sub-magnetic path wherein said coil is not wound about said magnetic core, a magnetic path formed along said magnetic core forming a configuration having a closed loop like configuration, and a maximum gain reduction ratio of a gain value shown by said antenna structure in a case where a metal object is present in the vicinity of said antenna structure to a gain value shown by said antenna structure in a case where said metal object is absent in the vicinity of said antenna structure, is not more than 60%.

27. (Original) An antenna structure according to claim 26, wherein said metal object including at least one of a dial plate of a timepiece, an outer casing, a motor, a movement, a battery, a solar battery, a wrist band, a heat sink, a microcomputer, a gear train, and said like.

28. (Original) An antenna structure according to claim 26, wherein said metal object is arranged at a position located with a certain distance from said antenna structure to which a magnetic flux output therefrom in a state wherein said sub-magnetic path is not added to said antenna structure can reach when said antenna structure receives said radio wave to produce resonance, and said metal object having a function of absorbing said magnetic flux.

29. (Original) An antenna structure for being able to receive a radio wave and which is arranged in a timepiece wherein at least one of a side section and a bottom cover section thereof is made of a metal material, said antenna structure being characterized in that an L value of said antenna structure is not more than 1600 mH and winding resistance of said antenna structure is not more than 1 K $\Omega$ .



30. (Original) An antenna structure according to claim 29, wherein said L value is not more than 800 mH and said winding resistance of said antenna is not more than 1 K $\Omega$ .

31. (Original) An antenna structure according to claim 29, wherein said L value is not more than 220 mH and said winding resistance of said antenna is not more than 1 K $\Omega$ .

32. (Cancelled)

33. (Cancelled)

34. (Cancelled)

35. (Original) An antenna structure according to claim 2, wherein said antenna structure which being able to receive a radio wave is arranged in a timepiece wherein at least one of a side section and a bottom cover section is made of a metal material, and said number of turns of said antenna is not lower than 400.

36. (Original) An antenna structure according to any one of claims 29 to 31, wherein said number of turns is not lower than 1000.

37. (Currently Amended) An antenna structure according to any one of claims 29 to 31 and ~~36~~, wherein a diameter of a winding wire is not more than 0.11 mm $\phi$ .

38. (Currently Amended) An antenna structure according to any one of claims 29 to 31 and ~~35 to 37~~, wherein said antenna structure for receiving said radio wave to be used inside a metal outer casing, said antenna structure comprises a main magnetic path wherein a coil is wound about a magnetic core and a sub-magnetic path wherein said coil is not wound about said magnetic core, said magnetic path formed along said magnetic core having a configuration of a closed loop like configuration, a gap is provided in a part of said magnetic path of said antenna structure having said closed loop like configuration, said gap is configured so as to have magnetic resistance or magnetic permeability which being different from magnetic resistance or magnetic of other part of said magnetic path other than said gap, and said antenna structure having a structure wherein a magnetic flux caused by an external radio wave coming into said metallic outer casing can be received but said magnetic flux generated by resonance hardly leaks to an outside of said magnetic path.

39. (Original) An antenna structure which receives a radio wave and comprising at least a magnetic core portion and a coil portion which is provided on at least one portion of said magnetic core portion, wherein, said antenna structure including a main magnetic path wherein a coil is wound about said magnetic core and a sub-magnetic path

wherein said coil is not wound about said magnetic core, said magnetic path along said magnetic core forming a configuration having a closed loop like configuration, said antenna structure being suitable to be used under circumstances wherein a metal material is present in the vicinity of said antenna structure, and a Q value retention ratio Rq defined below, in a case where said metal object is present in the vicinity of said antenna structure, is not lower than 10%,

wherein said Q value retention ratio Rq is expressed by said following equation:

$$Rq = Q_{NL}/Q_O \times 100,$$

where, the Q value of the antenna structure is set to  $Q_O$  in the case where the antenna structure is placed under an environment in which the antenna structure is not disposed in contact with the metal object or the metal object is absent in the vicinity of the antenna structure, and a Q values of the antenna structure are measured and set to  $Q_N$  in an environment where the antenna structure is disposed in contact with the metal object or the metal object is disposed in the vicinity of the antenna structure, and then the most lowest  $Q_N$  value is selected as  $Q_{NL}$ .

40. (Original) An antenna structure according to claim 39, wherein said Q value showing said minimum value in said Q values, wherein a plurality of kinds of metal

objects made of different metal materials are measured under said same condition, is selected as said minimum value  $Q_{NL}$  of said Q value of said antenna structure.

41. (Original) An antenna structure according to claim 40, wherein said minimum value  $Q_{NL}$  of said Q value of said antenna structure is a value which is measured under circumstances, wherein a metal object made of stainless steel (SUS), titanium, or a titanium alloy is connected to said antenna structure or said metal object is arranged in said vicinity of said antenna structure.

42. (Currently Amended) An antenna structure according to any one of claims ~~1 to 28~~, 39 to 41, wherein said magnetic path forming said closed loop like configuration, is said magnetic path which said magnetic flux generated by resonance passes through.

43. (Currently Amended) A radio control timepiece which comprises a reference signal generating means for outputting a reference signal; a time keeping means for outputting time keeping information on the basis of said reference signal; a displaying means for displaying a time information on the basis of said time keeping information; a receiving means for receiving standard radio wave having reference time information and a time information correction means for correcting the output time information output from said

time keeping means based on the receiving signal received from a receiving means, and wherein said receiving means including an antenna structure having the structure defined by any one of claims ~~1 to 42~~, 2, 26, 29 or 39.

44. (Original) A radio control timepiece according to claim 43, wherein said radio control timepiece has an outer casing unit which is made of said metal material.

45. (Original) A radio control timepiece according to claim 44, wherein at least one of said side section and said bottom cover section is made of said metal material.

46. (Currently Amended) A radio control timepiece according to ~~any one of claims 43 to 45~~claim 43, wherein said main magnetic path of said antenna structure is arranged in an outer periphery of said radio control timepiece and said sub-magnetic path is arranged inside said main magnetic path relative to said outer periphery of said radio control timepiece.

47. (Currently Amended) A radio control timepiece according to ~~any one of claims 43 to 46~~claim 45, wherein said antenna structure is provided on a surface of a dial plate of said radio control timepiece, said surface being opposite to another surface thereof which is facing to a windshield.

48. (Currently Amended) A radio control timepiece according to ~~any~~  
~~one of claims 43 to 47~~ claim 45, wherein said antenna structure is provided in said radio  
control timepiece, and further wherein at least a part of the portion of said sub-magnetic path  
of said antenna structure and which opposing to said outer casing unit of said radio control  
timepiece is covered with said main magnetic path.